



DTA Fast
29 Longfield Road
Leamington Spa
CV31 1XB

t: +44 (0) 1926 889121
e: office@dtafast.co.uk
w: www.dtafast.co.uk

S Series CAN Stream Specification

General

CAN bus Baud Rate	1 MBd
Identifiers	All 29Bit
6 Data Packets	All 8 Bytes Ea.
Send Frequency	10 - 50Hz

All Data Values 16 Bit Signed Sent LSB First (Little Endian)

Data Packets From V62.01

ID	Data1	Data2	Data3	Data4
0x2000	RPM	TPS %	Water Temp C	Air Temp C
0x2001	MAP Kpa	Lambda x 1000	KPH x 10	Oil P Kpa
0x2002	Fuel P Kpa	Oil Temp C	Volts x 10	Fuel Con. L/100Km x 10
0x2003	Gear	Advance Degx10	Injection ms x 100	Fuel Con. L/Hr x 10
0x2004	Ana1 mV	Ana2 mV	Ana3 mV	Cam Advance x 10
0x2005	Cam Targ x 10	Cam PWM x 10	Crank Errors	Cam Errors

From V79.02 the items below were added.

0x2006	Cam2 Adv x 10	Cam2 Targ x 10	Cam2 PWM x 10	External 5v
---------------	---------------	----------------	---------------	-------------

From V79.04 the items below were added.

0x2007	Inj Duty Cycle %	Lambda PID Targ	Lambda PID Adj
---------------	------------------	-----------------	----------------

From V86.04 the items below were added.

0x2007	Inj Duty Cycle %	Lambda PID Targ	Lambda PID Adj	ECU Switches
---------------	------------------	-----------------	----------------	--------------

From V87.01 the items below were added.

0x2008	RD Speed	RUD Speed	LD Speed	LUD Speed
0x2009	Right Lambda			



DTA Fast
29 Longfield Road
Leamington Spa
CV31 1XB

t: +44 (0) 1926 889121
e: office@dtafast.co.uk
w: www.dtafast.co.uk

ECU Switches

BIT VALUE

- 0 LAUNCH BUTTON PRESSED
- 1 LAUNCH ACTIVE
- 2 TRACTION ON
- 3 TRACTION WET
- 4 FUEL PUMP ON
- 5 FAN OUTPUT ON
- 6
- 7
- 8
- 9
- 10
- 11
- 12
- 13
- 14
- 15